

F2-D(WT)+RC2



3-Button WiFi & IR CCT LED Controller

- WiFi & IR 2 channel constant voltage CCT LED controller.
- 2A per channel, output connects with 5 meters CCT LED strip.
- 3 button operation with on/off, CCT and brightness adjustment.
- Tuya APP cloud control, support on/off, color temperature and brightness adjust, delay turn on/off light, timer run, scene edit function.
- Voice control, support for Amazon Alexa, Google Assistant, Tmall Genie and Xiaodu voice assistant.
- 4096 levels 0-100% dimming smoothly without any flash.




CE RoHS

Technical Parameters


Input and Output		Dimming data		Safety and EMC	
Input voltage	5-24VDC	Input signal	WiFi + IR + 3 button	EMC standard (EMC)	ETSI EN 301 489-1 V2.2.3 ETSI EN 301 489-17 V3.2.4
Output voltage	5-24VDC	Control distance	10m(Barrier-free space)	Safety standard	EN 61348-1:2015+A1:2021 EN 61348-2-13:2014+A1:2017
Output current	2CH,2A/CH	Dimming gray scale	4096 (2^12) levels	Certification	CE, EMC
Output power	20W@5V 48W@12V 96W@24V	Dimming range	0-100%	Package	
Environment		Dimming curve	Logarithmic	Size	L110 x W57 x H28mm
Operation temperature	Ta: -30°C ~ +50°C	PWM Frequency	2KHz (default)	Gross weight	0.086kg
Case temperature (Max.)	Tc: +85°C	Warranty	5 years		
		Protection	Over heat		

Mechanical Structures and Installations


Controller size:




Remote size:



Wiring Diagram



System wiring



Button function

- : Turn on or off light.
- : Adjust color temperature, short press to switch between 3 color temperatures (WW, NW and CW), long press 1-6s for continuous 256 levels adjustment.
- : Adjust brightness, short press 10 levels, long press 1-6s for continuous 256 levels adjustment.

Note:

1. Press and hold the and button for 2s, output LED flashes 3 times, the light on/off fade time will change between 3s and 0.5s.
2. Press and hold the , and button for 2s, output LED flashes multiple times, switch between "+, CW, WW" (flashes 1 times) and "+, WW CW" (flashes 2 times) output sequences, default is "+, CW, WW" order.

Key function of IR remote controller





- : Turn on/off the light.
- : Short press switch between 3 color temperature (warm white, neutral white, cool white).
- : Color temperature +/-, short press 10 levels, long press 1-6s for continuous 256 levels adjustment.
- : Brightness +/-, short press 10 levels, long press 1-6s for continuous 256 levels adjustment.
- : Brightness 10%.
- : Brightness 100%.



Notes:

1. The IR remote control does not need to be paired and can be controlled directly.
2. When the remote control distance is far, the infrared remote control needs to be aimed at the infrared reception head of the dimmer.

Tuya APP network connection

Please download the corresponding tuya/smart life app according to your region.

Press and hold  and  button for 2s:
clear previous network connection, enter Smart config mode, the output LED will flash 10 times.

Press and hold  and  button for 5s:
Clear previous network connection, enter AP config mode, the output LED will flash 5 times.
If smart config failed, please try AP config.

Repeat power on and off for 5 consecutive times, also clear previous network connection, enter Smart config mode, the output LED will flash 10 times.

If Tuya APP network connection succeed, the output LED will stop flash, and in Tuya APP, you can find CCTc device .




Smart life APP




Tuya Smart

Tuya APP interface





CCT interface

Touch color circle to adjust the color temperature.
Touch brightness slide to adjust brightness.



Scene interface

The 1-4 scene is static color.
the inner color of these scene can be editable.



Music, Schedule, Timer


The music play can use smart phone music player or micro-phone as music signal input.

The Schedule key can add multiple timers to turn on or turn off light according to different time periods.

The Timer key can turn on or turn off light in the next 24 hours.

Dimming Curve

Linear dual color tuning



Dimming curve

