


RF 1-4 Channels AC Switch

- High-voltage AC input, 4-channel high-voltage AC switch output.  
Per channel output current 5A, maximum total output power 1200W.
- Suitable for turning on/off single color LED lights, traditional incandescent and halogen lights.
- Set 1, 2, 3, 4 channel switch output by DIP switch.
- Match with RF 2.4G remote control.




CE RoHS emc RED

Technical Parameters

Input and Output		Safety and EMC		Environment	
Input voltage	100-240VAC	EMC standard(EMC)	ETSI EN 301 489-1 V2.2.3 ETSI EN 301 489-17 V3.2.4	Operation temperature	Ta: -20°C ~ +55°C
Output voltage	100-240VAC	Safety standard	EN 61347-1:2015+A1:2021 EN 61347-2-13:2014+A1:2017	Case temperature (Max.)	Tc: +75°C
Output current	4CH, 5A/CH	Radio equipment(RED)	ETSI EN 300 328 V2.2.2	IP rating	IP 20
Output power	500-1200W/CH	Certification	CE, EMC, RED	<b>Package</b>	
Input signal	RF 2.4GHz	Warranty	5 years	Size	L187 x W60 x H40mm
Control distance	30m(Barrier-free space)			Gross weight	0.192kg

Mechanical Structures and Installations




DIP Switch Setting

Set 1/2/3/4 channel switch output by DIP switch:

	1 channel output, L1, L2, L3, L4 synchronized switch, match with single-zone or multiple-zone remote control.
	2 channel output, L1 and L3 synchronized switch, L2 and L4 synchronized switch, match with 2 zones remote control.
	3 channel output, L1, L2, L3 independently switch, L4 invalid, match with 4 zones remote control.
	4 channel output, L1, L2, L3, L4 independently switch, match with 4 zones remote control.

## Wiring Diagram

Taking set to 4 channel output and match with 4-zone switch remote control for example, zones 1,2,3, 4 of the remote control correspond to L1, L2, L3, L4 switch respectively.



## Match with RF Remote Controller

There are two ways to match/delete:

### Use Match key

Match:

Short press match key, the LED indicator flash slowly. immediately press on/off key (single zone remote) or zone key (multiple zone remote) of the remote. the LED indicator fast flash 3 times means match is successful.

Delete:

Press and hold match key for 5s to delete all match, The LED indicator fast flash a few times means all matched remotes were deleted.

### Use Power Restart

Match:

Switch off the power, then switch on power, repeat again. Immediately short press on/off key (single zone remote) or zone key (multiple zone remote) 3 times on the remote. The light indicator blinks 3 times means match is successful.

Delete:

Switch off the power, then switch on power, repeat again. Immediately short press on/off key (single zone remote) or zone key (multiple zone remote) 5 times on the remote. The light indicator blinks 5 times means all matched remotes were deleted.

## Recommended Remote Controls



R1-1

Single zone switch remote control



PF1-2

2 zone switch remote control



RK4-U

4 zone switch remote control



RU4

4 zone switch remote control