







### Single Color Constant Voltage LED Controller

Model Name	Product Name	Pictrue	Parameters	Key Feature	Recommended Products	Distinguish Between Similar Products
E1-C	Touch Dimming Single Color Constant Voltage LED Controller		Input/Output voltage:12-24VDC Output power:Max.36W@12V Max.72W@24V PWM frequency:128Hz Proudct size:50x7.8x10mm(LxWxH)	<ul style="list-style-type: none"> <li>● Red and Black wire inputs and outputs,connect with 5 meters single color LED strip.</li> <li>● Highly sensitive touch operation with LED indicators.</li> <li>● Short press to turn on or off the light,long press to adjust the brightness.</li> <li>● The media on the touch spring can be PC cover,acrylic board or mirror glass.</li> </ul>	/	/
EC-AV	Touch Dimming Single Color Constant Voltage LED Controller		Input/Output voltage:5-24VDC Output current:2.5A Output power:Max.30W@12V Max.60W@24V PWM frequency:125Hz(default) Proudct size:20x18.5mm(DxH)	<ul style="list-style-type: none"> <li>● Dupont wire male input, Dupont wire female output.</li> <li>● Highly sensitive touch operation with LED indicators.</li> <li>● Short press to turn on or off the light,long press to adjust the brightness.</li> <li>● Four PWM frequencies (125,500,2K,8KHz) are set by pressing multiple times in quick succession at the moment of power-up.</li> <li>● Concealed installation, bilateral snap design,applied to staircase,cabinet,closeet, wine cooler and other lighting.</li> </ul>	LED Control Box:CVO	/
Q1-S	3 button Single color constant voltage LED controller		Input/Output voltage:12-24VDC Output current:Max.4A Dimming curve:Logarithmic PWM frequency:750Hz Proudct size:60x12.5x3mm(LxWxH)	<ul style="list-style-type: none"> <li>● Red and Black wire input and output,connect with 5 meters single color LED strip.</li> <li>● 3 buttons operation with on/off and dimming.</li> </ul>	/	/
V1-D	DIP Dimming Single Color Constant Voltage LED Controller		Input/Output voltage:12-24VDC Output current:Max.6A Dimming range:10-100% Dimming curve:Logarithmic PWM frequency:1KHz,8KHz Proudct size:55x13x4mm(LxWxH)	<ul style="list-style-type: none"> <li>● Red and Black wire input and output,connect with 5 meters single color LED strip.</li> <li>● Setting of light brightness, on/off fade time,output PWM frequency via 6-position Dip switch.</li> <li>● 8 levels of brightness(10-100%).</li> <li>● 4 level light on/off fade time(0/1/2/4s) selectable.</li> <li>● 2 types of output PWM frequency(1K/8KHz) selectable.</li> </ul>	/	/

### Color Temperature Constant Voltage LED Controller

Model Name	Product Name	Pictrue	Parameters	Key Feature	Recommended Products	Distinguish Between Similar Products
Q2-S	3 button Color Temperature Constant Voltage LED Controller		Input/Output voltage:12-24VDC Output current:2A/CH,Total Max.4A Dimming curve:Linear PWM frequency:750Hz Proudct size:60x12.5x3mm(LxWxH)	<ul style="list-style-type: none"> <li>● Red and black wire input,three-wire output,connecting 5 meters of color temperature LED low voltage strip.</li> <li>● 3 butons to achieve on/off and dimming and color temperature adjustment.</li> </ul>	/	/

### RGB Constant Voltage LED Controller

Model Name	Product Name	Pictrue	Parameters	Key Feature	Recommended Products	Distinguish Between Similar Products
Q3-S	3 button RGB Constant Voltage LED Controller		Input/Output voltage:12-24VDC Output current:1.5A/CH,Total Max.4.5A Dimming curve:Linear PWM frequency:750Hz Proudct size:60x12.5x3mm(LxWxH)	<ul style="list-style-type: none"> <li>● Red and black wire input,four-wire output,connects to 5 meters of RGB LED low voltage light tape.</li> <li>● 3 buttons for on/off,mode and color adjustment.</li> <li>● Built-in 10 dynamic modes,including jumps and fades.</li> </ul>	/	/