


























RF RGB/RGBW Constant Voltage LED Controller





| Model Name | Product Name | Pictrue | Parameters | Key Feature | Recommended Products | Distinguish Between Similar Products |
|------------|---|---|--|--|--|---|
| V3 | RF Dimming 3 Channel Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:3x(12-24)VDC Output current:3CH,4A/CH Input signal:RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:1KHz Product size:97x33x18mm(LxWxH) | <ul style="list-style-type: none"> ● RF dimming LED controller,3 channel constant voltage outputs. ● 3 in 1 function,used for control single color,color temperature or RGB LED low-voltage strips. ● Match with RF 2.4G single zone or multiple zone dimming,color temperature and RGB/RGBW remote control. ● When using with RGB light, built in 10 dynamic mode, include jump or gradual change style. ● Light on/off fade time 3s selectable. | RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 RGB Panel RF Remote Control:RK3, TW4, T24, T13S, T13, T13-K | / |
| V3-L | RF+Push Dimming 3 Channel Constant Voltage LED Controller |  | Input voltage:12-48VDC Output voltage:3x(12-48)VDC Output current:3CH,6A/CH Input signal:RF 2.4GHz, Push Dim Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:1KHz Product size:175x45x27mm(LxWxH) | <ul style="list-style-type: none"> ● RF dimming LED controller,3 channel constant voltage outputs. ● 3 in 1 function,used for control single color,color temperature or RGB LED low-voltage strips. ● Match with RF 2.4G single zone or multiple zone dimming,color temperature and RGB/RGBW remote control. ● Connect with 3 external push switch to achieve on/off and 0-100% dimming function. ● When using with RGB light, built in 10 dynamic mode, include jump or gradual change style. ● Light on/off fade time 3s selectable. | RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 RGB Panel RF Remote Control:RK3, TW4, T24, T13-S, T13, T13-K | / |
| VD3 | RF Dimming RGB Constant Voltage LED Controller |  | Input voltage:5-24VDC Output voltage:3x(5-24)VDC Output current:3CH,1.5A/CH Input signal:3 button,RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:2KHz(default) Product size:73x35x14mm(LxWxH) | <ul style="list-style-type: none"> ● 3 channel constant voltage RGB LED RF controller. ● 3 buttons to realize the switch and mode and color adjustment. ● Match with RF 2.4G single zone or multi zone RGB remote control. ● Built in 10 dynamic mode, include jump or gradual change style. | RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 RGB Panel RF Remote Control:RK3, TW4, T24, T13-S, T13, T13-K | / |
| V3-C | RF Dimming RGB Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:3x(12-24)VDC Output current:3x6A@500Hz/2KHz 3x5A@8KHz/16KHz Input signal:3 button,RF 2.4GHz,Push Dim Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:500Hz,2KHz,8KHz,16KHz Product size:90x40x28mm(LxWxH) | <ul style="list-style-type: none"> ● 3 channel constant voltage RGB LED RF controller. ● Switching on/off and dimming of light and color via 3 buttons. ● Match with RF 2.4G single zone or multi zone RGB remote control. ● Built in 10 dynamic mode, include jump or gradual change style. ● DIP switch selects 4 PWM frequency(500/2K/8K/16KHz). | RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 RGB Panel RF Remote Control:RK3, TW4, T24, T13-S, T13, T13-K | / |
| V3-M | RF Dimming RGB Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:3x(12-24)VDC Output current:2A/CH,Total Max.6A Input signal:RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:2KHz Product size:76x23.5x8.7mm(LxWxH) | <ul style="list-style-type: none"> ● 3 channel constant voltage RGB LED RF controller. ● Red and black wire input, 4-color flat wire output. ● 2A per channel, output connect with 5 meters RGB LED strip. ● Match with RF 2.4G single zone or multi zone RGB remote control. ● Built in 10 dynamic mode, include jump or gradual change style. ● Light on/off fade time 3s selectable. | RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 RGB Panel RF Remote Control:RK3, TW4, T24, T13-S, T13, T13-K | |
| V3-M(CJ) | RF Dimming RGB Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:3x(12-24)VDC Output current:2A/CH,Total Max.6A Input signal:RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:2KHz Product size:76x23.5x8.7mm(LxWxH) | <ul style="list-style-type: none"> ● 3 channel constant voltage RGB LED RF controller. ● Red and black wire input, 4-pin flat male jack output. ● 2A per channel, output connect with 5 meters RGB LED strip. ● Match with RF 2.4G single zone or multi zone RGB remote control. ● Built in 10 dynamic mode, include jump or gradual change style. ● Light on/off fade time 3s selectable. | RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 RGB Panel RF Remote Control:RK3, TW4, T24, T13-S, T13, T13-K | <p>V3-M, V3-M(CJ), V3-M(DJ) Contrast:</p> <p>Common: The functions and parameters are consistent.</p> <p>Difference: Power and LED connectors are different. V3-M Power connector:Red/Black Cable 10cm LED connector:4-color Flat Cable 10cm V3-M(CJ)Power connector:Red/Black Cable 10cm LED connector:4-pin Flat male Jack 10cm V3-M(DJ)Power connector:5.5mm DC Female Jack LED connector:4-pin Flat male Jack 10cm</p> |
| V3-M(DJ) | RF Dimming RGB Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:3x(12-24)VDC Output current:2A/CH,Total Max.6A Input signal:RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:2KHz Product size:76x23.5x8.7mm(LxWxH) | <ul style="list-style-type: none"> ● 3 channel constant voltage RGB LED RF controller. ● DC female input, 4 pin flat male jack output. ● 2A per channel, output connect with 5 meters RGB LED strip. ● Match with RF 2.4G single zone or multi zone RGB remote control. ● Built in 10 dynamic mode, include jump or gradual change style. ● Light on/off fade time 3s selectable. | RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 RGB Panel RF Remote Control:RK3, TW4, T24, T13-S, T13, T13-K | |

| | | | | | | |
|----------|--|---|---|---|--|--|
| V3-W | RF Dimming RGB Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:3x(12-24)VDC Output power:Max. 75W Input signal:RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:500Hz Product size:60x14x4mm(LxWxH) | <ul style="list-style-type: none"> ● 3 channel constant voltage RGB LED RF controller. ● Red and black wire input, 4-color flat wire output. ● 1A per channel, output connect with 5 meters RGB LED strip. ● Match with RF 2.4G single zone or multi zone RGB remote control. ● Built in 10 dynamic mode, include jump or gradual change style. | RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 RGB Panel RF Remote Control:RK3, TW4, T24, T13-S, T13, T13-K | |
| V3-W(CJ) | RF Dimming RGB Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:3x(12-24)VDC Output power:Max. 75W Input signal:RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:500Hz Product size:60x14x4mm(LxWxH) | <ul style="list-style-type: none"> ● 3 channel constant voltage RGB LED RF controller. ● Red and black wire input, 4-color flat female jack output. ● 1A per channel, output connect with 5 meters RGB LED strip. ● Match with RF 2.4G single zone or multi zone RGB remote control. ● Built in 10 dynamic mode, include jump or gradual change style. | RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 RGB Panel RF Remote Control:RK3, TW4, T24, T13-S, T13, T13-K | V3-W, V3-W(CJ), V3-W(DJ) Contrast: Common: The functions and parameters are consistent. Difference: Power and LED connectors are different. V3-W Power connector:Red/Black Cable 10cm LED connector:4-color Flat Cable 10cm V3-W(CJ) Power connector:Red/Black Cable 10cm LED connector:4-pin Flat Female Jack V3-W(DJ) Power connector:5.5mm DC Female Jack LED connector:4-pin Flat Female Jack |
| V3-W(DJ) | RF Dimming RGB Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:3x(12-24)VDC Output power:Max. 75W Input signal:RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:500Hz Product size:60x14x4mm(LxWxH) | <ul style="list-style-type: none"> ● 3 channel constant voltage RGB LED RF controller. ● DC female input, 4 pin flat female jack output. ● 1A per channel, output connect with 5 meters RGB LED strip. ● Match with RF 2.4G single zone or multi zone RGB remote control. ● Built in 10 dynamic mode, include jump or gradual change style. | RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 RGB Panel RF Remote Control:RK3, TW4, T24, T13-S, T13, T13-K | |
| VP | RF Dimming 4 Channel Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:4x(12-24)VDC Output current:4CH, 4A/CH, Max 6A Input signal:RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:1KHz Product size:114x38x20mm(LxWxH) | <ul style="list-style-type: none"> ● RF dimming LED controller, DC power socket input and 4 channel constant voltage output. ● 4 in 1 function, used for control single color, color temperature or RGB/RGBW LED low-voltage strips. ● Match with RF 2.4G single zone or multiple zone dimming, color temperature and RGB/RGBW remote control. ● When using with RGB/RGBW light, built in 10 dynamic mode, include jump or gradual change style. ● Light on/off fade time 3s selectable. | RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | |
| V4 | RF+Push Dimming 4 Channel Constant Voltage LED Controller |  | Input voltage:12-48VDC Output voltage:4x(12-48)VDC Output current:4CH, 5A/CH Input signal:RF 2.4GHz, Push Dim Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:1000Hz Product size:175x45x27mm(LxWxH) | <ul style="list-style-type: none"> ● RF dimming LED controller, 4 channel constant voltage output. ● 4 in 1 function, used for control single color, color temperature or RGB/RGBW LED low-voltage strips. ● Match with RF 2.4G single zone or multiple zone dimming, color temperature and RGB/RGBW remote control. ● Connect with 4 external push switch to achieve on/off and 0-100% dimming function. ● When using with RGB/RGBW light, built in 10 dynamic mode, include jump or gradual change style. ● Light on/off fade time 3s selectable. | RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | / |
| V4-S | RF+Push Dimming 4 Channel Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:4x(12-24)VDC Output current:4CH, 3A/CH Input signal:RF 2.4GHz, Push Dim Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:1KHz (default) Product size:52x52x26mm(LxWxH) | <ul style="list-style-type: none"> ● RF + Push LED controller, 4 channel constant voltage output. ● 4 in 1 function, used for control RGB, RGBW, color temperature or single-color LED low-voltage strips. ● Set as single color, dual color, RGB or RGBW controller by DIP switch. ● Match with RF 2.4G single color, dual color and RGB/RGBW remote control. ● Connect with push switch to achieve on/off and 0-100% dimming function. ● Easy to be placed in standard wall junction box. | RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | / |
| VD4 | RF Dimming RGBW Constant Voltage LED Controller |  | Input voltage:5-24VDC Output voltage:4x(5-24)VDC Output current:4CH, 1.5A/CH Input signal:3 button, RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:2KHz Product size:73x35x14mm(LxWxH) | <ul style="list-style-type: none"> ● 4 channel constant voltage RGBW LED RF controller. ● 3 keys to realize the switch and mode and color adjustment. ● Match with RF 2.4G single zone or multi zone RGBW remote control. ● Built in 10 dynamic mode, include jump or gradual change style. | RGBW RF Remote Control:R14, R8-1, R8, RT4, RT9, RS4 RGBW Panel RF Remote Control:TW4, T24, T14-S, T14 | / |
| V4-L | RF+Push Dimming 4 Channel Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:4x(12-24)VDC Output current:4CH, 5A/CH Input signal:3 button, RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic/linearly PWM frequency:1KHz (default) Product size:170x50x23mm(LxWxH) | <ul style="list-style-type: none"> ● RF dimming LED controller, 4 channel constant voltage output. ● Digital numeric display and 3 button operation. ● 5-in-1 function, can be set to 1-channel dimmer, 4 channel dimmer, dual color temperature, RGB or RGBW controller. ● Match with RF 2.4G single zone or multiple zone dimming, color temperature and RGB/RGBW remote control. ● 4 PWM frequency can be set (1K/2K/4K/8KHz). ● Logarithmic or linear dimming curve selectable. ● Light on/off fade time 0.5/2/3/5/10/20s selectable. ● When using with RGB/RGBW light, built in 10 dynamic mode, include jump or gradual change style. | RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | / |





| | | | | | | |
|----------|---|---|--|--|--|---|
| V4-K | RF+Knob Dimming RGB/RGBW Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:4x(12-24)VDC Output current:4CH, 4A/CH Input signal:Knob, 3 button, RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:1KHz(default) Product size:187x46x35.5mm (LxWxH) | <ul style="list-style-type: none"> ● RGB/RGBW constant voltage LED RF controller, also can be used as an RGB/RGBW RF remote control. ● 4 knob dimming, digital numeric display and easy key operation. ● Match with RF 2.4G single zone or multiple zone RGB/RGBW remote control optional. ● 4 PWM frequency can be set (1K/2K/4K/8KHz). ● Logarithmic or linear dimming curve selectable. ● Built in 10 dynamic mode, include jump or gradual change style. | RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | / |
| V4-X | RF+Push Dimming 4 Channel Constant Voltage LED Controller |  | Input voltage:12-48VDC Output voltage:4x(12-48)VDC Output current:4CH, 8A/CH@12-24V 5A/CH@36-48V Input signal:RF 2.4GHz Control distance:15m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:1KHz Product size:117x85x24.5mm (LxWxH) | <ul style="list-style-type: none"> ● RF dimming LED controller, 4 channel constant voltage output. ● 4 in 1 function, used for control RGB, RGBW, color temperature or single-color LED low-voltage strips. ● Match with RF 2.4G single zone or multiple zone dimming, color temperature and RGB/RGBW remote control. ● When using with RGB/RGBW light, built in 10 dynamic mode, include jump or gradual change style. ● Light on/off fade time 3s selectable. | RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | / |
| V4-WPS | Waterproof RF Dimming 4 Channel Constant Voltage LED Controller |  | Input voltage:12-36VDC Output voltage:4x(12-36)VDC Output current:4CH, 5A/CH Input signal:RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:1KHz(default) Product size:153x57x34mm (LxWxH) | <ul style="list-style-type: none"> ● 4 channel constant voltage LED RF dimming controller. ● 4 in 1 function, used for control RGB, RGBW, color temperature or single-color LED low-voltage strips. ● Match with RF 2.4G single color, dual color and RGB/RGBW remote control. ● When using with RGB/RGBW light, built in 10 dynamic mode, include jump or gradual change style. ● Waterproof to IP67 for outdoor and humid environments. | RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | / |
| V4-M | RF Dimming RGBW Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:4x(12-24)VDC Output current:1.5A/CH, Total Max. 6A Input signal:RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:2KHz(default) Product size:76x23.5x8.7mm (LxWxH) | <ul style="list-style-type: none"> ● 4 channel constant voltage RGBW LED RF controller. ● Red and black wire input, 5-color flat wire output. ● 1.5A per channel, output connect with 5 meters RGBW LED strip ● Match with RF 2.4G single zone or multiple zone RGBW remote control optional. ● Built in 10 dynamic mode, include jump or gradual change style. ● Light on/off fade time 3s selectable. | RGBW RF Remote Control:R14, R8-1, R8, RT4, RT9, RS4 RGBW Panel RF Remote Control:TW4, T24, T14-S, T14 | |
| V4-M(CJ) | RF Dimming RGBW Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:4x(12-24)VDC Output current:1.5A/CH, Total Max. 6A Input signal:RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:2KHz(default) Product size:76x23.5x8.7mm (LxWxH) | <ul style="list-style-type: none"> ● 4 channel constant voltage RGBW LED RF controller. ● Red and black wire input, 5-pin flat male jack output. ● 1.5A per channel, output connect with 5 meters RGBW LED strip ● Match with RF 2.4G single zone or multiple zone RGBW remote control optional. ● Built in 10 dynamic mode, include jump or gradual change style. ● Light on/off fade time 3s selectable. | RGBW RF Remote Control:R14, R8-1, R8, RT4, RT9, RS4 RGBW Panel RF Remote Control:TW4, T24, T14-S, T14 | V4-M, V4-M(CJ), V4-M(DJ) Contrast: Common: The functions and parameters are consistent. Difference: Power and LED connectors are different. V4-M Power connector:Red/Black Cable 10cm LED connector:5-color Flat Cable 10cm V4-M(CJ) Power connector:Red/Black Cable 10cm LED connector:5-pin Flat male Jack 10cm V4-M(DJ) Power connector:5.5mm DC Female Jack LED connector:5-pin Flat male Jack 10cm |
| V4-M(DJ) | RF Dimming RGBW Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:4x(12-24)VDC Output current:1.5A/CH, Total Max. 6A Input signal:RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:2KHz(default) Product size:76x23.5x8.7mm (LxWxH) | <ul style="list-style-type: none"> ● 4 channel constant voltage RGBW LED RF controller. ● DC female input, 5 pin flat male jack output. ● 1.5A per channel, output connect with 5 meters RGBW LED strip ● Match with RF 2.4G single zone or multiple zone RGBW remote control optional. ● Built in 10 dynamic mode, include jump or gradual change style. ● Light on/off fade time 3s selectable. | RGBW RF Remote Control:R14, R8-1, R8, RT4, RT9, RS4 RGBW Panel RF Remote Control:TW4, T24, T14-S, T14 | |
| V4-W | RF Dimming RGBW Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:4x(12-24)VDC Output power:Max. 75W Input signal:RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:500Hz(default) Product size:60x14x4mm (LxWxH) | <ul style="list-style-type: none"> ● 4 channel constant voltage RGBW LED RF controller. ● Red and black wire input, 5-color flat wire output. ● 1A per channel, output connect with 5 meters RGBW LED strip ● Match with RF 2.4G single zone or multiple zone RGBW remote control optional. ● Built in 10 dynamic mode, include jump or gradual change style. | RGBW RF Remote Control:R14, R8-1, R8, RT4, RT9, RS4 RGBW Panel RF Remote Control:TW4, T24, T14-S, T14 | |
| V4-W(CJ) | RF Dimming RGBW Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:4x(12-24)VDC Output power:Max. 75W Input signal:RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:500Hz(default) Product size:60x14x4mm (LxWxH) | <ul style="list-style-type: none"> ● 4 channel constant voltage RGBW LED RF controller. ● Red and black wire input, 5 pin flat female jack output. ● 1A per channel, output connect with 5 meters RGBW LED strip ● Match with RF 2.4G single zone or multiple zone RGBW remote control optional. ● Built in 10 dynamic mode, include jump or gradual change style. | RGBW RF Remote Control:R14, R8-1, R8, RT4, RT9, RS4 RGBW Panel RF Remote Control:TW4, T24, T14-S, T14 | V4-W, V4-W(CJ), V4-W(DJ) Contrast: Commonalities: The functions and parameters are consistent. Difference: Power and LED connectors are different. V4-W Power connector:Red/Black Cable 10cm LED connector:5-color Flat Cable 10cm V4-W(CJ) Power connector:Red/Black Cable 10cm LED connector:5-pin Flat Female Jack V4-W(DJ) Power connector:5.5mm DC Female Jack LED connector:5-pin Flat Female Jack |
| V4-W(DJ) | RF Dimming RGBW Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:4x(12-24)VDC Output power:Max. 75W Input signal:RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:500Hz(default) Product size:60x14x4mm (LxWxH) | <ul style="list-style-type: none"> ● 4 channel constant voltage RGBW LED RF controller. ● DC female input, 5 pin flat female jack output. ● 1.5A per channel, output connect with 5 meters RGBW LED strip ● Match with RF 2.4G single zone or multiple zone RGBW remote control optional. ● Built in 10 dynamic mode, include jump or gradual change style. | RGBW RF Remote Control:R14, R8-1, R8, RT4, RT9, RS4 RGBW Panel RF Remote Control:TW4, T24, T14-S, T14 | |

| | | | | | | |
|------|--|---|--|--|--|---|
| V5-L | RF+Push Dimming 5 Channel Constant Voltage LED Controller |  | <p>Input voltage:12-48VDC Output voltage:5x(12-48)VDC Output current:6A/CH@12-24V 4A/CH@36-48V Input signal:RF 2.4GHz, Push Dim Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:2KHz(default) Product size:179x56x30mm(LxWxH)</p> | <ul style="list-style-type: none"> ● RF+Push dimming LED controller,5-channel constant voltage outputs. ● 5 in 1 function, used for control RGB, RGBW, RGB+CCT, color temperature or single color low voltage LED strip. ● DIP switch to select color temperature,RGB, RGBW or RGB+CCT four light types. ● Match with RF 2.4G single zone or multiple zone dimming,color temperature,RGB,RGBW or RGB+CCT RF remote control. ● Built in 10 dynamic mode, include jump or gradual change style. ● 4 PWM frequencies can be set (500/2K/8K/16KHz). ● Light on/off fade time 3s selectable. | <p>RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14</p> | / |
|------|--|---|--|--|--|---|


WiFi+RF Constant Voltage LED Controller


| Model Name | Product Name | Pictrue | Parameters | Key Feature | Recommended Products | Distinguish Between Similar Products |
|------------|--|---|--|---|--|--------------------------------------|
| WT5 | WiFi+RF 5 Channel Constant Voltage LED Controller |  | <p>Input voltage:12-24VDC Output voltage:5x(12-24)VDC Output current:5CH, 3A/CH Input signal:WiFi, RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:1KHz(default) Product size:114x38x20mm(LxWxH)</p> | <ul style="list-style-type: none"> ● 5 channel constant voltage output,used for control RGB, RGBW, RGB+CCT,color temperature or single color LED strip. ● 5 in 1 function,press the button to switch RGB,RGBW, RGB+CCT,color temperature or single color light types. ● Tuya APP cloud control,support on/off,RGB color,color temperature and brightness adjust,delay turn on/off light,timer run,scene edit and music play function. ● Voice control,support for Amazon Alexa,Google Assistant,Tmall Genie and Xiaodu smart speakers. ● Match with RF 2.4G single zone or multiple zone remote control of the same light type optional. ● Can be used as a WiFi-RF signal converter to control other RF LED controller. ● Connect with push switch to achieve on/off and 0-100% dimming function. ● Light on/off fade time 3s selectable. | <p>RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14</p> | / |
| V5-L(WT) | WiFi+RF 5 Channel Constant Voltage LED Controller |  | <p>Input voltage:12-48VDC Output voltage:5x(12-48)VDC Output current:6A/CH@12/24V 4A/CH@36/48V Input signal:WiFi,RF2.4GHz, Push Dim Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:2KHz(default) Product size:179x56x30mm(LxWxH)</p> | <ul style="list-style-type: none"> ● 5 channel constant voltage output,used for control RGB, RGBW, RGB+CCT,color temperature or single color LED strip. ● 5 in 1 function,DIP switch set RGB, RGBW, RGB+CCT, color temperature or single color light type. ● Tuya APP cloud control,support on/off,RGB color,color temperature and brightness adjust,delay turn on/off light,timer run,scene edit and music play function. ● Voice control,support for Amazon Alexa,Google Assistant,Tmall Genie and Xiaodu smart speakers. ● Match with RF 2.4G single zone or multiple zone remote control of the same light type optional. ● Can be used as a WiFi-RF signal converter to control other RF LED controller. ● Connect with push switch to achieve on/off and 0-100% dimming function. ● 500,2000,8000,16000Hz output PWM frequency settable. ● Light on/off fade time 3s selectable. | <p>RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14</p> | / |
| VD3(WT) | WiFi+RF RGB Constant Voltage LED Controller |  | <p>Input voltage:5-24VDC Output voltage:3x(5-24)VDC Output current:3CH, 1.5A/CH Input signal:3 button,WiFi, RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:2KHz(default) Product size:73x35x14mm(LxWxH)</p> | <ul style="list-style-type: none"> ● 3 channel constant voltage output,used for control RGB LED low voltage strip. ● Three buttons to realize the switch and mode and color adjustment. ● Tuya APP cloud control,support on/off,RGB color,color temperature and brightness adjust,delay turn on/off light,timer run,scene edit and music play function. ● Voice control,support for Amazon Alexa,Google Assistant,Tmall Genie and Xiaodu smart speakers. ● Match with RF 2.4G single zone or multiple zone RGB remote control optional. ● Built-in 10 dynamic modes,including jumps and fades. | <p>RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 RGB Panel RF Remote Control:RK3, TW4, T24, T13-S, T13, T13-K</p> | / |
| VD4(WT) | WiFi+RF RGBW Constant Voltage LED Controller |  | <p>Input voltage:5-24VDC Output voltage:4x(5-24)VDC Output current:4CH, 1.5A/CH Input signal:3 button,WiFi, RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:2KHz(default) Product size:73x35x14mm(LxWxH)</p> | <ul style="list-style-type: none"> ● 4 channel constant voltage output,used for control RGBW LED low voltage strip. ● Three buttons to realize the switch and mode and color adjustment. ● Tuya APP cloud control,support on/off,RGB color,color temperature and brightness adjust,delay turn on/off light,timer run,scene edit and music play function. ● Voice control,support for Amazon Alexa,Google Assistant,Tmall Genie and Xiaodu smart speakers. ● Match with RF 2.4G single zone or multiple zone RGBW remote control optional. ● Built-in 10 dynamic modes,including jumps and fades. | <p>RGBW RF Remote Control:R14, R8-1, R8, RT4, RT9, RS4 RGBW Panel RF Remote Control:TW4, T24, T14-S, T14</p> | / |

Zigbee+RF Constant Voltage LED Controller






| Model Name | Product Name | Pictrue | Parameters | Key Feature | Recommended Products | Distinguish Between Similar Products |
|------------|--|---|---|--|--|--------------------------------------|
| WZ5 | Zigbee 3.0+RF 5 Channel Constant Voltage LED Controller |  | Input/Output voltage:12-24VDC Output current:5CH, 3A/CH Input signal:Zigbee 3.0, RF 2.4GHz Control distance:30m(Barrier-free space) PWM frequency:1KHz(default) Dimming curve:Logarithmic Proudct size:114x38x20mm(LxWxH) | <ul style="list-style-type: none"> ● 5 channel constant voltage output,used for control RGB, RGBW, RGB+CCT,color temperature or single color LED strip. ● 5 in 1 function,press button to switch RGB, RGBW, RGB+CCT,color temperature or single color light type. ● Tuya APP cloud control, support on/off,RGB color,color temperature and brightness adjust,delay turn on/off light,timer run,scene edit and music play function. ● Philips HUE APP control by connect with Philips HUE bridge. ● Voice control,support for Amazon Alexa,Google Assistant,Tmall Genie and Xiaodu smart speakers. ● Match with single or multi-zone RF 2.4G remote control of the same light type optional. ● Can be used as a Zigbee-RF signal converter to control other RF LED controllers. ● Light on/off fade time 3s selectable. | Zigbee scene panel:PK8(WZS), PK4(WZS), TS4(WZS) Zigbee gateway:WG-Z RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | / |
| V5-L(WZ) | Zigbee 3.0+RF 5 Channel Constant Voltage LED Controller |  | Input voltage:12-48VDC Output voltage:5x(12-48)VDC Output current:6A/CH@12/24V 4A/CH@36/48V Input signal:Zigbee 3.0+Push switch+RF2.4GHz Control distance:30m(Barrier-free space) PWM frequency:2KHz(default) Dimming curve:Logarithmic Proudct size:179x56x30mm(LxWxH) | <ul style="list-style-type: none"> ● 5 channel constant voltage output,used for control RGB, RGBW, RGB+CCT,color temperature or single color LED strip. ● 5 in 1 function,DIP switch set RGB, RGBW, RGB+CCT, color temperature or single color light type. ● Tuya APP cloud control, support on/off,color temperature and brightness adjust,delay turn on/off light,timer run,scene edit and music play function. ● Philips HUE APP control by connect with Philips HUE bridge. ● Voice control,support for Amazon Alexa,Google Assistant,Tmall Genie and Xiaodu smart speakers. ● Match with single or multi-zone RF 2.4G remote control of the same light type optional. ● Can be used as a Zigbee-RF signal converter to control other RF LED controllers. ● PWM frequency 500Hz, 2000Hz, 8000Hz or 16000Hz selectable. ● Connect with external push switch to achieve on/off and dimming function. ● Light on/off fade time 3s selectable. | Zigbee scene panel:PK8(WZS), PK4(WZS), TS4(WZS) Zigbee gateway:WG-Z RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | / |
| VD3(WZ) | WiFi+RF RGB Constant Voltage LED Controller |  | Input voltage:5-24VDC Output voltage:3x(5-24)VDC Output current:3CH, 1.5A/CH Input signal:3 button,Zigbee 3.0, RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:2KHz(default) Product size:73x35x14mm(LxWxH) | <ul style="list-style-type: none"> ● 3 channel constant voltage output,used for control RGB LED low voltage strip. ● 3 buttons to realize the switch and mode and color adjustment. ● Tuya APP cloud control, support on/off,brightness adjust,delay turn on/off light,timer run,scene edit function. ● Philips HUE APP control by connect with Philips HUE bridge. ● Voice control, support for Amazon Alexa,Tmall Genie. ● Match with single zone or multiple zone RGB remote control optional. ● Built in 10 dynamic mode, include jump or gradual change style. | RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 RGB RGBW Panel RF Remote Control:RK3, TW4, T24, T13-S, T13, T13-K | / |
| VD4(WZ) | WiFi+RF RGBW Constant Voltage LED Controller |  | Input voltage:5-24VDC Output voltage:4x(5-24)VDC Output current:4CH, 1.5A/CH Input signal:3 button,Zigbee 3.0, RF 2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:2KHz(default) Product size:73x35x14mm(LxWxH) | <ul style="list-style-type: none"> ● 4 channel constant voltage output,used for control RGBW LED low voltage strip. ● 3 buttons to realize the switch and mode and color adjustment. ● Tuya APP cloud control, support on/off,brightness adjust,delay turn on/off light,timer run,scene edit function. ● Philips HUE APP control by connect with Philips HUE bridge. ● Voice control, support for Amazon Alexa,Tmall Genie. ● Match with single zone or multiple zone RGBW remote control optional. ● Built in 10 dynamic mode, include jump or gradual change style. | RGBW RF Remote Control:R14, R8-1, R8, RT4, RT9, RS4 RGBW Panel RF Remote Control:TW4, T24, T14-S, T14 | / |

Bluetooth+RF Constant Voltage LED Controller


| Model Name | Product Name | Pictrue | Parameters | Key Feature | Recommended Products | Distinguish Between Similar Products |
|------------|---|---|--|---|--|--------------------------------------|
| WB5 | Bluetooth+RF 5 Channel Constant Voltage LED Controller |  | Input voltage:12-24VDC Output voltage:5x(12-24)VDC Output current:5CH, 3A/CH Input signal:Bluetooth+RF2.4GHz Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:1KHz(default) Proudct size:114x38x20mm(LxWxH) | <ul style="list-style-type: none"> ● 5 channel constant voltage output,used for control RGB, RGBW, RGB+CCT,color temperature or single color LED strip. ● 5 in 1 function,press button to switch RGB, RGBW, RGB+CCT,color temperature or dimming light type. ● Tuya APP cloud control, support on/off, RGB color,color temperature and brightness adjust,delay turn on/off light,timer run,scene edit and music play function. ● Voice control, support for Amazon Alexa, Google Assistant, Tmall Genie and Xiaodu smart speakers. ● Match with single or multi-zone RF 2.4G remote control of the same light type optional. ● Can be used as a Bluetooth-RF signal converter to control other RF LED controllers. ● Light on/off fade time 3s selectable. | Bluetooth Gateway:WG-B RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | / |


| | | | | | | |
|----------|---|---|---|--|--|---|
| V5-L(WB) | Bluetooth+RF 5 Channel Constant Voltage LED Controller |  | <p>Input voltage:12-24VDC Output voltage:5x(12-48)VDC Output current:6A/CH@12/24V 4A/CH@36/48V</p> <p>Input signal:Bluetooth+RF2.4GHz+Push Dim Control distance:30m(Barrier-free space) Dimming curve:Logarithmic PWM frequency:2KHz(default) Proudct size:179x56x30mm(LxWxH)</p> | <ul style="list-style-type: none"> ● 5 channel constant voltage output,used for control RGB, RGBW, RGB+CCT,color temperature or single color LED strip. ● 5 in 1 function, DIP switch set RGB,RGBW,RGB+CCT, color temperature or dimming light type. ● Tuya APP cloud control,support on/off,RGB color,color temperature and brightness adjust, delay turn on/off light,timer run,scene edit and music play function. ● Voice control, support for Amazon Alexa, Google Assistant, Tmall Genie and Xiaodu smart speakers. ● Match with single or multi-zone RF 2.4G remote control of the same light type optional. ● Can be used as a Bluetooth-RF signal converter to control other RF LED controllers. ● PWM frequency 500Hz,2000Hz,8000Hz or 16000Hz selectable. ● Light on/off fade time 3s selectable. ● Connect with external push switch to achieve on/off and 0-100% dimming function. | Bluetooth Gateway:WG-B RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | / |
|----------|---|---|---|--|--|---|

RF RGB/RGBW Constant Voltage LED Panel Controller

| Model Name | Product Name | Pictrue | Parameters | Key Feature | Recommended Products | Distinguish Between Similar Products |
|------------|---|---|--|--|---|--------------------------------------|
| T3-K | RF RGB Constant Voltage LED Rotary Panel Controller |  | <p>Input voltage:12-48VDC Output voltage:3x(12-48)VDC Output current:3CH, 4A/CH Input signal:RF 2.4GHz Control distance:10m(Barrier-free space) PWM frequency:2K/8KHz Proudct size:86x86x48mm(LxWxH)</p> | <ul style="list-style-type: none"> ● Short press knob switch, rotate knob to adjust color or brightness (double-click to switch). ● DIP switch to select 2 PWM frequency(2K/8KHz). ● Match with RF 2.4G single zone or multi zone RGB remote control. ● Can be used as a low voltage powered single zone RGB RF remote control. ● Blue indicator is displayed during operation. ● White & Black available. | RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 | / |
| T3 | RF RGB Constant Voltage LED Touch Panel Controller |  | <p>Input voltage:12-24VDC Output voltage:3x(12-24)VDC Output current:3CH, 4A/CH Input signal:RF 2.4GHz Control distance:10m(Barrier-free space) PWM frequency:1KHz Proudct size:86x86x33mm(LxWxH)</p> | <ul style="list-style-type: none"> ● Touch the color wheel to adjust the color. ● Match with RF 2.4G single zone or multi zone RGB remote control. ● Can be used as a low voltage powered single zone RGB RF remote control. ● Red and blue indicator is displayed during operation. ● White & Black available. | RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 | / |
| T3-1 | RF RGB Constant Voltage LED Touch Panel Controller |  | <p>Input voltage:12-24VDC Output voltage:3x(12-24)VDC Output current:3CH, 4A/CH Input signal:RF 2.4GHz Control distance:10m(Barrier-free space) PWM frequency:1KHz Proudct size:86x86x33mm(LxWxH)</p> | <ul style="list-style-type: none"> ● Touch the color slide to adjust the color. ● 4 scene memory. ● Match with RF 2.4G single zone or multi zone RGB remote control. ● Can be used as a low voltage powered single zone RGB RF remote control. ● Red and blue indicator is displayed during operation. ● White & Black available. | RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 | / |
| T4 | RF RGBW Constant Voltage LED Touch Panel Controller |  | <p>Input voltage:12-24VDC Output voltage:4x(12-24)VDC Output current:4CH, 3A/CH Input signal:RF 2.4GHz Control distance:10m(Barrier-free space) PWM frequency:1KHz Proudct size:86x86x33mm(LxWxH)</p> | <ul style="list-style-type: none"> ● Touch the color wheel to adjust the color. ● 4 scene memory. ● Match with RF 2.4G single zone or multi zone RGBW remote control. ● Can be used as a low voltage powered single zone RGBW RF remote control. ● Red and blue indicator is displayed during operation. ● White & Black available. | RGBW RF Remote Control:R14, R8-1, R8, RT4, RT9, RS4 | / |
| T4-1 | RF RGBW Constant Voltage LED Touch Panel Controller |  | <p>Input voltage:12-24VDC Output voltage:4x(12-24)VDC Output current:4CH, 3A/CH Input signal:RF 2.4GHz Control distance:10m(Barrier-free space) PWM frequency:1KHz Proudct size:86x86x33mm(LxWxH)</p> | <ul style="list-style-type: none"> ● Touch the color slide to adjust the color. ● 4 scene memory. ● Match with RF 2.4G single zone or multi zone RGBW remote control. ● Can be used as a low voltage powered single zone RGBW RF remote control. ● Red and blue indicator is displayed during operation. ● White & Black available. | RGBW RF Remote Control:R14, R8-1, R8, RT4, RT9, RS4 | / |

RF Constant Current LED Controller





| Model Name | Product Name | Pictrue | Parameters | Key Feature | Recommended Products | Distinguish Between Similar Products |
|---------------|--|---|---|--|--|--------------------------------------|
| C4(150-500mA) | RF+Push Dimming 4 Channel Constant Current LED Controller |  | <p>Input voltage:12-48VDC Output voltage:4x(3-45)VDC Output current:4CH, 150-500mA/CH Input signal:RF 2.4GHz, Push Dim Control distance:30m(Barrier-free space) Dimming curve:Logarithmic Proudct size:175x45x27mm(LxWxH)</p> | <ul style="list-style-type: none"> ● RF+Push dimming LED controller, 4 channel constant current output, 8 levels current selectable. ● 4 in 1 function,used for control single color, color temperature, RGB or RGBW constant current LED light. ● DIP switch set single color, color temperature,RGB or RGBW four light types. ● Match with RF 2.4G single zone or multiple zone single color, dual color and RGB/RGBW remote control. ● Connect with external push switch to achieve on/off and 0-100% dimming function. ● When using with RGB/RGBW light, built in 10 dynamic mode, include jump or gradual change style. ● Fade in and out effect selectable. | RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | / |

| | | | | | | |
|----------------|--|---|---|--|--|---|
| C4(350-1200mA) | RF+Push Dimming 4 Channel Constant Current LED Controller |  | Input voltage:12-48VDC Output voltage:4x(3-45)VDC Output current:350-1200mA/CH Input signal:RF 2.4GHz,Push Dim Control distance:30m(Barrier-free space) Dimming curve:Logarithmic Proudct size:175x45x27mm(LxWxH) | <ul style="list-style-type: none"> ● RF+Push dimming LED controller, 4 channel constant current output, 8 levels current selectable. ● 4 in 1 function,used for control single color, color temperature, RGB or RGBW constant current LED light. ● DIP switch set single color, color temperature,RGB or RGBW four light types. ● Match with RF 2.4G single zone or multiple zone single color, dual color and RGB/RGBW remote control. ● Connect with external push switch to achieve on/off and 0-100% dimming function. ● When using with RGB/RGBW light, built in 10 dynamic mode, include jump or gradual change style. ● Fade in and out effect selectable. | RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | / |
|----------------|--|---|---|--|--|---|

RF High Voltage LED Controller

| Model Name | Product Name | Pictrue | Parameters | Key Feature | Recommended Products | Distinguish Between Similar Products |
|------------|--|---|---|---|---|--------------------------------------|
| S3 | RF+Push Dimming 3-Channel High Voltage LED Strip Controller |  | Input voltage:100-240VAC Output voltage:3x(100-240)VDC Output current:3CH, 1A/CH Input signal:RF 2.4GHz, AC Push Switch Control distance:30m(Barrier-free space) PWM frequency:2KHz Proudct size:175x45x27mm(LxWxH) | <ul style="list-style-type: none"> ● 3 in 1 function, used for control RGB, color temperature or single color high voltage LED strip. ● Match with RF 2.4G single zone or multiple zone single color, dual color and RGB remote control. ● Connect with external push switch to achieve on/off and 0-100% dimming function. ● When using with RGB light, built in 10 dynamic mode, include jump or gradual change style. ● Light on/off fade time 3s selectable. | RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 RGB Panel RF Remote Control:RK3, TW4, T24, T13-S, T13, T13-K | / |
| S3(WT) | WiFi+RF 3-Channel High Voltage LED Strip Controller |  | Input voltage:100-240VAC Output voltage:3x(100-240)VDC Output current:3CH, 1A/CH Input signal:RF 2.4GHz, AC Push Switch Control distance:30m(Barrier-free space) PWM frequency:2KHz Proudct size:175x45x27mm(LxWxH) | <ul style="list-style-type: none"> ● 3 in 1 function, used for control RGB, color temperature or single color high voltage LED strip. ● Press the button to switch RGB, color temperature or single color light types. ● Tuya APP cloud control,support on/off,RGB color,color temperature and brightness adjust,delay turn on/off light,timer run,scene edit and music play function. ● Voice control, support for Amazon Alexa, Google Assistant, Tmall Genie and Xiaodu smart speakers. ● Match with RF 2.4G single zone or multiple zone single color, dual color and RGB remote control. ● Connect with external push switch to achieve on/off and 0-100% dimming function. ● When using with RGB light, built in 10 dynamic mode, include jump or gradual change style. ● Light on/off fade time 3s selectable. | RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 RGB Panel RF Remote Control:RK3, TW4, T24, T13-S, T13, T13-K | / |
| S3-DX | 3 Channel High Voltage LED Strip DMX512 & RDM Decoder |  | Input voltage:110-240VAC Output voltage:3x(110-240)VDC Output current:3CH, 1.5A/CH Input signal:DMX512, RF 2.4GHz Control distance:15m(Barrier-free space) Proudct size:165x70x37mm(LxWxH) | <ul style="list-style-type: none"> ● Digital numeric display, set DMX decode start address by buttons. ● 1/3 DMX channel output selectable. ● Supports RDM funtion. ● Supports 3 DMX signal ports:Green terminal, XLR3 and RJ45. ● PWM frequency 1000/2000/4000/8000Hz selectable. ● Logarithmic or linear dimming curve selectable. ● Can be used as a standalone 3-channel dimmer controller or RGB controller. ● Match with RF 2.4G single zone or multiple zone RGB remote control optional. ● Built-in 10 RGB change modes with adjustable speed and brightness. | DMX512 Console:Channel dimming,dynamic effect edit DMX Master Control panel:T13-4S, T13, T13-K WiFi APP Control:WT-DMX-S Zigbee Control:WZ-DMX-S RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 RGB Panel RF Remote Control:RK3, TW4, T24, T13-S, T13, T13-K | / |
| S4-DX | 4 Channel High Voltage LED Strip DMX512 & RDM Decoder |  | Input voltage:110-240VAC Output voltage:4x(110-240)VDC Output current:4CH, 2A/CH Input signal:DMX512, RF 2.4GHz Control distance:15m(Barrier-free space) Proudct size:201x119x38mm(LxWxH) | <ul style="list-style-type: none"> ● Digital numeric display, set DMX decode start address by buttons. ● 1/2/4 DMX channel output selectable. ● Supports RDM funtion. ● Supports 3 DMX signal ports:Green terminal, XLR3 and RJ45. ● PWM frequency 1000/2000/4000/8000Hz selectable. ● Logarithmic or linear dimming curve selectable. ● Can be used as a standalone 4-channel dimmer controller or RGB/RGBW controller. ● Match with RF 2.4G single zone or multiple zone RGB/RGBW remote control optional. ● Built-in 4 RGBW change modes with adjustable speed and brightness. | DMX512 Console:Channel dimming,dynamic effect edit DMX Master Control panel:T13-4S, T13, T13-K WiFi APP Control:WT-DMX-S Zigbee Control:WZ-DMX-S RGB RF Remote Control:R13, R8-1, R8, RT4, RT9, RS4 RGB Panel RF Remote Control:RK3, TW4, T24, T13-S, T13, T13-K | / |

RF Constant Voltage LED Driver

| Model Name | Product Name | Pictrue | Parameters | Key Feature | Recommended Products | Distinguish Between Similar Products |
|-------------|--|---|---|---|--|--------------------------------------|
| PB-75-12-4 | RF+Push Dimming 75W 12V 4 Channel Constant Voltage LED Driver |  | Input voltage:200-240VAC Output voltage:12VDC Output current:4x1.56A Output power:Max.75W Input signal:RF 2.4GHz,AC Push Switch Control distance:30m(Barrier-free space) PWM frequency:1KHz Proudct size:179x56x30mm(LxWxH) | <ul style="list-style-type: none"> ● Dimming interface:RF 2.4G, AC Push Switch. ● 4 channel constant current output, Max.total output power 75W. ● 4 in 1 function,used for control single color,color temperature,RGB or RGBW LED low voltage strip. ● Match with RF 2.4G single zone or multiple zone single color, dual color and RGB/RGBW remote control. ● Connect with external push switch to achieve on/off and 0-100% dimming function. ● When using with RGB/RGBW light,built in 10 dynamic mode, include jump or fade change style. ● Fade in and out effect selectable. | RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | / |
| PB-75-24-4 | RF+Push Dimming 75W 24V 4 Channel Constant Voltage LED Driver |  | Input voltage:200-240VAC Output voltage:24VDC Output current:4x0.78A Output power:Max.75W Input signal:RF 2.4GHz,AC Push Switch Control distance:30m(Barrier-free space) PWM frequency:1KHz Proudct size:179x56x30mm(LxWxH) | <ul style="list-style-type: none"> ● Dimming interface:RF 2.4G, AC Push Switch. ● 4 channel constant current output, Max.total output power 75W. ● 4 in 1 function,used for control single color,color temperature,RGB or RGBW LED low voltage strip. ● Match with RF 2.4G single zone or multiple zone single color, dual color and RGB/RGBW remote control. ● Connect with external push switch to achieve on/off and 0-100% dimming function. ● When using with RGB/RGBW light,built in 10 dynamic mode, include jump or fade change style. ● Fade in and out effect selectable. | RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | / |
| PH-150-12-4 | RF+Push Dimming 150W 12V 4 Channel Constant Voltage LED Driver |  | Input voltage:100-240VAC Output voltage:12VDC Output current:4x3.12A Output power:Max.150W Power factor:>0.95 Input signal:RF 2.4GHz,AC Push Switch Control distance:30m(Barrier-free space) PWM frequency:1KHz Proudct size:280x67x36mm(LxWxH) | <ul style="list-style-type: none"> ● Dimming interface:RF 2.4G, AC Push Switch. ● 4 channel constant current output, Max.total output power 150W. ● 4 in 1 function,used for control single color,color temperature,RGB or RGBW LED low voltage strip. ● Match with RF 2.4G single zone or multiple zone single color, dual color and RGB/RGBW remote control. ● Connect with external push switch to achieve on/off and 0-100% dimming function. ● When using with RGB/RGBW light,built in 10 dynamic mode, include jump or fade change style. ● Fade in and out effect selectable. | RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | / |
| PH-150-24-4 | RF+Push Dimming 150W 24V 4 Channel Constant Voltage LED Driver |  | Input voltage:100-240VAC Output voltage:24VDC Output current:4x1.56A Output power:Max.150W Power factor:>0.95 Input signal:RF 2.4GHz,AC Push Switch Control distance:30m(Barrier-free space) PWM frequency:1KHz Proudct size:280x67x36mm(LxWxH) | <ul style="list-style-type: none"> ● Dimming interface:RF 2.4G, AC Push Switch. ● 4 channel constant current output, Max.total output power 150W. ● 4 in 1 function,used for control single color,color temperature,RGB or RGBW LED low voltage strip. ● Match with RF 2.4G single zone or multiple zone single color, dual color and RGB/RGBW remote control. ● Connect with external push switch to achieve on/off and 0-100% dimming function. ● When using with RGB/RGBW light,built in 10 dynamic mode, include jump or fade change style. ● Fade in and out effect selectable. | RGB/RGBW RF Remote Control:R13, R14, R8-1, R8, RT4, RT9 RGB/RGBW Panel RF Remote Control:TW4, T24, T13-S, T14 | / |