# 3 Channel Constant Current DMX512 & RDM Decoder

## Model No.: D3C-L(350mA) / D3C-L(700mA)

RDM/Stand-alone function/Two PWM frequency/Linear or logarithmic dimming/Numeric display



#### Features

C CE RoHS emc LVD

- Comply with the DMX512 standard protocols.
- Digital numeric display, set DMX decode start address by buttons.
- RDM function can realize intercommunication between DMX master and decoder. For example, DMX decoder address can be set by DMX master console.
- PWM frequency 2000/500Hz selectable.
- Logarithmic or linear dimming curve selectable.
- Stand-alone RGB mode and 3 channel dimmer mode selectable, which be controlled by buttons with built-in programs, instead of DMX signal.

#### **Technical Parameters**


Input and Output		
Input voltage	12-48VDC	
Output voltage	3 x (3-46)VDC	
Output current	3CH,350mA or 700mA/CH	
Output power	3 x (1.05-16.1)W (350mA) 3 x (2.1-32.2)W (700mA)	
Output type	Constant current	
Safety and EMC		
EMC standard (EMC)	EN55032:2015, EN61000-3-2:2014, EN61000-3-2:2013, EN55024 :2010/A1:2015	
Safety standard(LVD)	EN 61347-1:2015 EN 61347-2-11:2015	
Certification	CE,EMC,IVD	


Environment	
Operation temperature	Ta: -30 °C ~ +55 °C
Case temperature (Max.)	Tc:+85°C
IP rating	IP20

Warranty and Protection				
Warranty	5 years			
Protection	Reverse Polarity Short circuit			


Weight	
Net weight	0.150kg
Gross weight	0.167kg

### Mechanical Structures and Installations





## Wiring Diagram



#### Note:

- 1. The LED quantity at each channel can be different, the decoder could auto check and output a proper voltage to each channel according to its LED quantities.
- 2. The decoder works on buck mode, the voltage of power supply should be greater than the total voltage of the seried LEDs.
- 3. An DMX signal amplifier is needed if more than 32 decoders are connected, or use overlong signal line, signal amplification should not be more than 5 times continuously.
- 4. If the recoil effect occurs because of longer signal line or bad line quality, please try to connect 0.25W 90-120 $\Omega$  terminal resistor at the end of each DMX signal line.

## Operation

#### System parameter setting

- Long press M and < key in the same time for 2s, prepare for setup system parameter: output PWM frequence, output brightness curve, automatic blank screen. short press M key to switch three item.
- Output PW/M frequence: short press < or > key to switch 500Hz("F-L") or 2KHz("F-H").
- Output brightness curve: short press ◀ or ► key to switch linear curve("C-L") or logarithmic curve("C-E").
- Automatic blank screen: short press ◀ or ➤ key to switch enable ("bon") or disable("boF") automatic blank screen.
- Long press M key for 2s or timeout 10s, quit system parameter setting.

#### DMX mode

• Short press M key, when display 001~999, enter DMX mode



 $(001 \sim 999)$ 

 Press 

 r r r r r key to change DMX decode start address(001~999), long press for fast adjustment.

- If there is a DMX signal input, will enter DMX mode automatically.
- DMX Dimming: Each D3C-L DMX decoder occupy 3 DMX address when connecting the DMX console

For example, the defaulted start address is 1, their corresponding relationship in the form:

MX Console	DMX Decoder Output	
CH1 0-255	CH1 PW/M 0-100% (LED R)	
CH2 0-255	CH2 PW/M 0-100% (LED G)	
CH3 0-255	CH3 PW/M 0-100% (LED B)	

### Stand-alone RGB mode

- Enter stand-alone RGB mode only when DMX signal is disconnected or lost.
- Short press M key, when display PO1~P30, enter stand-alone RGB mode.
- Press ◀ or ▶ key to change dynamic mode number(P01~P30).
- Each mode can adjust speed and brightness.

Long press M key for 2s, prepare for setup mode speed and brightness. Short press M key to switch two item.

Press  $\blacktriangleleft$  or  $\blacktriangleright$  key to setup value of each item.

Mode speed: 1-10 level speed(S-1, S-9, S-F). Mode brightness: 1-10 level brightness(b-1, b-9, b-F).

Long press M key for 2s, or timeout 10s, quit setting.

### Stand-alone dimmer mode

- Enter stand-alone dimmer mode only when D/WX signal is disconnected or lost.
- Short press M key, when display L-1 ~L-8, enter stand-alone dimmer mode.
- Press ◄ or ► key to change dimmer mode number(L-1~L-8).
- Each dimmer mode can adjust each channel brightness independently. Long press M key for 2s, prepare for setup three channel brightness.
   Short press M key to switch three channel(100~1FF, 200~2FF, 300~3FF).
   Press • ar > key to setup brightness value of each channel.
   Long press M key for 2s, or timeout 10s, quit setting.



Stand-alone RGB mode (P01~P30)





#### Stand-alone dimmer mode (L-1~L-8)

#### Restore factory default parameter


- Long press ◀ and ▶ key for 2s, restore factory default parameter, display"RES"
- Factory default parameter: DMX decode mode, DMX decode start address is 1, high PWM frequence output, logarithmic brightness curve, RGB mode number is 1, dimmer mode number is 1, disable automatic blank screen.

## RGB change mode list


No.	Name	No.	Name	No.	Name
PO1	Static red	P11	Green strobe	P21	Red yellow smooth
PO2	Static green	P12	Blue strobe	P22	Green cyan smooth
PO3	Static blue	P13	White strobe	P23	Blue purple smooth
PO4	Static yellow	P14	RGB strobe	P24	Blue white smooth
PO5	Static cyan	P15	7 color strobe	P25	RGB+W smooth
P06	Static purple	P16	Red fade in and out	P26	RGBW smooth
P07	Static white	P17	Green fade in and out	P27	RGBY smooth
PO8	RGB jump	P18	Blue fade in and out	P28	Yellow cyan purple smooth
P09	7 color jump	P19	White fade in and out	P29	RGB smooth
P10	Red strobe	P20	RGBW fade in and out	P30	6 color smooth

## Dimming curve setting

Linear dimming curve



# Logarithmic dimming curve



## Malfunctions analysis & troubleshooting

	Malfunctions Causes		Troubleshooting	
No light         1. No power.           2. Wrong connection or insecure.           Wrong color         1. Wrong connection of R/G/B wires.           2. DWX decode address error.			<ol> <li>Check the power.</li> <li>Check the connection.</li> </ol>	
			<ol> <li>Reconnect R/G/B wires.</li> <li>Set corrrect decode address.</li> </ol>	